

# Licensed Electrician's Theory (LET) Assessment Marking Guide

Sample Paper April 2026

## AS/NZS 3000:2018 Electrical installations – Wiring Rules

### Question 1

7 [2 marks]

Clause 3.12.2.2 (a) [2 marks]

### Question 2

All active conductors. [2 marks]

Clause 4.7.1 [2 marks]

### Question 3

4mm<sup>2</sup>. [2 marks]

Clause 3.4.3 (a) [2 marks]

### Question 4

National Building Codes. [2 marks]

Clause 3.9.3.1 [2 marks]

## AS/NZS 3012:2019 Electrical installations – Construction and demolition sites

### Question 5

Any external forces that may be exerted on the switchboard. [2 marks]

Clause 2.3.3 [2 marks]

### Question 6

No. [2 marks]

Clause 2.5.7 [2 marks]

## Electrical Safety (General) Regulations 2019

### Question 7

No. [2 marks]

Regulation 239 (1) (a) [2 marks]

## Electrical Shock Survival

### Question 8

- (i) Observe if the is chest rising or listen for breaths (or similar wording)
- (ii) Check for a pulse

[2 + 2 = 4 marks]

## Cable Selection

### Question 9

Part (i)

	Answer		Answer		Mark(s)
Table 3 (___?)	3	Item	4		1 mark
Table	14	Column	23	Answer	2 marks
De/rating table: Spacing	25(2)	Column	4	Factor	0.84 1 mark
De/rating table: Depth	28(1)	Column	2	Factor	0.94 1 mark
<b>Calculations:</b> 3 cables in parallel $480 / 3 = 160$ per cable $50\text{mm}^2 = 204\text{A}$ $204 \times 0.84 \times 0.94 = 161.08\text{A}$ maximum demand $161.08\text{A} \times 3 = 483.23\text{A}$					
<b>Answer:</b> $50\text{mm}^2$					2 marks

Part (ii)

	Answer		Answer		Answer	Mark(s)
De/rating table: Depth	28(1)	Column	3	Factor	0.88	1 mark
<b>Calculations:</b> 3 cables in parallel $480 / 3 = 160$ per cable $70\text{mm}^2 = 251\text{A}$ $251 \times 0.84 \times 0.88 = 185.54\text{A}$ maximum demand $185.54 \times 3 = 556.62\text{A}$						
<b>Answer:</b> $70\text{mm}^2$						

Deduct 1 mark for no or incorrect units.

[1 + 2 + 1 + 1 + 2 + 1 = 8 marks]

## Ohms Law

## Question 10

- (i) Meter X = 1600W [3 marks]
- (ii) Meter Y = 2A [3 marks]
- (iii) Meter Z = 75Ω [3marks]

Deduct 1 mark for no or incorrect units.

[3 + 3 + 3 = 9 marks]

## Maximum Demand

### Question 11

Table C2 Column 3

2 - 6kW electric vehicle charger

1 - 4.5kW Oven

18 - 12W LED downlights

1 - 15A socket outlet

4 - 10A double socket outlets

### Single domestic

Table C2 Column 3 [1 mark]

Equipment	Load Group	Calculation	Maximum Demand
2 – 6kW electric vehicle chargers	(c) (ii)	Full connected load if highest rated + 75% of remainder $(6000 + (6000 \times 0.75)) / 230 = 45.65A$	45.65A [2 marks]
1 – 4.5kW oven	(c) (i)	Full connected load $4500 / 230 = 19.57A$	19.57A [1 mark]
18 – 12W LED downlights	(a)	Full connected load $(18 \times 12) / 230 = 0.94$	0.94A [1 mark]
1 – 15A socket outlet	(b)(iii)	Full current rating of highest rated socket outlet 15 A	15A [1 mark]
4 – 10A double socket outlets	(b)(i)	1000W for first outlet + 750W for each additional outlet $(1000 + (750 \times 7)) / 230 = 27.17A$	27.17A [1 mark]
<b>Total Maximum Demand</b>			<b>108.33A [1 mark]</b>

Deduct 1 mark for no or incorrect units on total. Deduct 1 mark for no or incorrect load groups.

[1+ 2+ 1 + 1 + 1 + 1 + 1 = 8 marks]

## Voltage Drop

### Question 12

Cable	Table	Column	Vc	Calculation	Vd
Consumer's Mains	T 41	Col 10	1.25 [1 mark]	$V_d = \frac{11 \times 130 \times 1.25}{1000}$	1.79V [1 mark]
	[1 mark]				
Sub-Mains	T 41	Col 8	2.55 [1 mark]	$V_d = \frac{22 \times 48 \times 2.55}{1000}$	2.69V [1 mark]
	[1 mark]				
Final Sub-Circuit	T 42	Col 6	6.49 [1 mark]	$V_d = \frac{25 \times 22 \times 6.49}{1000}$	3.57V [1 mark]
	[1 mark]				
<b>Answer Total Voltage Drop</b>			1.79 + 2.69 + 3.57		8.05V [1 mark]

Deduct 1 mark for no or incorrect units on total. Deduct 1 mark for no or incorrect table number/s.

[1+1+1+1+1+1+1+1+1+1 = 10 marks]

## Overload and Short Circuit Calculations

### Question 13

Overcurrent divided by MCB current rating:	2 [1 mark]		
Minimum Time:	Accept 22 – 27 seconds [1 mark]	Maximum Time:	110 – 120 seconds [1 mark]

Deduct 1 mark for no or incorrect time unit.

[1 + 1 + 1 = 3 marks]

### Question 14

	Calculation	Answer
Transformer Impedance:	230 / 20000 [2 marks]	**0.01150Ω [1 mark]
Main switchboard:	230 / (0.0115 + 0.00534) [2 marks]	13,658A [1 mark]
Distribution Board:	230 / (0.0115 + 0.00534 + 0.08191) [2 marks]	2329A [1 mark]

\*\*Answer should be to 5 decimal places, if the final number is zero, then 4 places is acceptable. 0.0115

Deduct 1 mark for no or incorrect units in final answer.

[(2+1) + (2+1) + (2+1) = 9 marks]

## Residual Current Devices

### Question 15

#### Option 1

18A [2 marks]

d) 20A [1 mark]

[2 + 1 = 3 marks]

#### Option 2

d) No devices will trip [2 marks]

a) Yes [1 mark]

[2 + 1 = 3 marks]

## Motor and Starters

### Question 16

d) lose starting torque and will not start. [2 marks]

## AS/NZS 4836:2023 Safe working on or near low-voltage and extra-low voltage electrical installations and equipment

### Question 17

After they have been provided evidence that the plant or equipment is safe to operate. [2 marks]

Clause number: 3.1.4.3.4 [2 marks]

## Installation Defects – Non-Domestic

### Question 18

2 marks for correct defect, 1 mark for the correct clause.

**Only some of the defects have been listed below, there are more than 10 defects in the diagram.**

All correct defects and clauses will be awarded marks.

Only accept the first 4 defects a candidate has listed.

- 1) Isolating switch labelled Main Switch not Isolating Switch 2.3.4.4
- 2) The 10A CB not labelled to identify the equipment it is protecting 2.10.5.2
- 3) 10A circuit is not protected by an RCD 2.6.3.2.3.3
- 4) The sump pump conductor undersized cables Clause 3.4.1

- 5) Neutral and active cables are not arranged to identify the corresponding circuit in the terminal bar. 2.10.5.4
- 6) Access to switchboard is blocked by other equipment 2.10.2.2.1 (a)
- 7) Minimum distance of 1 meter from all faces of a closed switchboard is not provided. 2.10.2.2.1 (b) (i)
- 8) MEN located at Main Switchboard, MEN installed in Distribution board not required Clause 5.3.5.1
- 9) Car charger does not have an earth conductor installed Clause 5.4.1.1 (a)

[4 x (2 + 1) = 12 marks]

SAMPLE